

DIGISTART 300

Ref. 10070



❓ The **DIGISTART 300** by Solter is a professional charger and starter designed for **12V and 24V batteries**, ideal for workshops and automotive professionals. Its **10-stage charging cycle** ensures efficient and safe charging, while its **repair mode** allows the recovery of sulfated or inactive batteries. With a **charging capacity of up to 300Ah** and a **starting power of 200A**, this device is perfect for keeping batteries in **optimal condition**. Additionally, it features **advanced safety measures**, ensuring reliable use. **Efficiency, power, and safety in one device!**

Main Features:

- ❓ **Powerful charging and starting:** Provides a **charging current of up to 40A** and a starting capacity of **200A**, ideal for batteries up to 300Ah.
- ❓ **Repair mode for sulfated batteries:** If your battery has lost performance, its **advanced recovery** function helps restore it.
- ❓ **Smart 10-stage charging:** Prevents overcharging and maximizes battery lifespan with a **fully automated and safe process**.
- ❓ **Full compatibility:** Works with **WET, GEL, MF, EFB, and AGM** batteries, ensuring versatility for multiple applications.
- ❓ **Protection against electrical risks:** Prevents short circuits and overheating with a safe design and certified quality.
- ❓ **Safe and risk-free charging:** Its **IP33** design and safety systems prevent damage from water, short circuits, or improper handling.
- ❓ **Safe storage and transport:** Compact and lightweight (**290x600x250mm, 17.5kg**), with a **robust and durable design** for professional use.
- ❓ **Complies with European regulations:** Manufactured according to **EN60335, EN55014, EN61000** standards, ensuring safety and reliability.
- ❓ **Protection against incorrect connection:** If the clamps are connected incorrectly, the charger detects the error and prevents damage.
- ❓ **Quick emergency start:** In case of a low battery, it allows a **safe and efficient start in just a few seconds**.
- ❓ **Trust Solter** to get equipment designed with the highest quality, safety, and performance for the automotive sector.

DIGISTART 300

Ref. 10070



TECHNICAL DATA

OPTIONAL ACCESSORIES

Generals

Regulations EN60335, EN55014, EN61000

Technical

Capacidad de carga max. 300Ah

Corriente de carga Arith. (DC 12V), 5A/15A/30A/40A o (DC 24V), 5A/15A/30A/40A

Tipo batería WET (plomo-ácido), GEL, MF, EFB, AGM,

Voltaje de arranque 12/24V

Voltaje de carga 12/24V

Capacidad de arranque 200A

Protección fugas Sí, detección de conexión incorrecta

Fuente alimentación Conectado a red eléctrica

Structural

Dimensions 290x600x250mm

Protection index IP33

Weight 17,5kg

Electrical

Supply Voltage 220-240VAC 50/60Hz

Absorbed power max. 3000W Max.(cargador), 9000W Max. (arranque)